Safety and emergency lighting systems







Scope of application

Safety / Emergency / Evacuation / Hydrants highlighting / Public lighting

Description

Ined is an emergency kit for LED lighting devices of up to 50W.

Adaptable to the inside or outside mounting to the lighting device, with DC adapter and LEDs supplied at 230 VAC.

Advantages

The emergency kit detects any failure of the normal power supply and begins to generate the voltage required to supply the LED lamps.

Fitting

Metal fitting.

General Information

Voltage: 220-240 VAC / 50 Hz Operating temperature: -10 / +50



ta					
Power ^[W]	Luminosity ^[Lm]	Efficiency ^[Lm / W]	Colour Temp. ^[k]	Dimensions ^[mm]	Weight ^[kg]
				151x42	0.9
					Power ^[W] Luminosity ^[Lm] Efficiency ^[Lm / W] Colour Temp. ^[k] Dimensions ^[mm]

Accessories

Product code	Suspension system	Application system	Embedding clips	Emergency kit	0-10V Dim. driver	DALI Driver	Sensor
ML03				YES			

Similar products

	Mobility
3W	
7W	1

Swing		
	2W	
€ []		

Mobility		
	2W	
<u>↑</u> [2]		

Orion Clip		
-	ЗW	
3		

